

Technical specifications

Communication with control panel or range extender	 Jeweller communication technology Frequency bands 866.0-866.5 MHz 868.0-868.6 MHz 868.7-869.2 MHz 905.0-926.5 MHz 915.85-926.5 MHz 921.0-922.0 MHz Depends on the region of sales. Maximum effective radiated power (ERP) Upto 20 mW Communication range up to 1,300 m Without obstacles.	Compatibility	Hubs all Ajax hubs Range extenders all Ajax radio signal range extenders
Compliance with special fire standards	EN 50131 (Grade 2) PD 6662:2017	Features	4 buttons Arm Disarm Night mode Panic Panic button can be deactivated by PRO or a user with admin rights in the Ajax apps. LED indication green and red SpaceControl reports its status only after any button is pressed. Protection against accidental press double or long press Configured by the PRO or user with admin rights in the Ajax apps.

Anti-sabotage protection	Protection against spoofing device authentication	Power supply	1 x CR2032 battery Up to 5 years of battery life.
Enclosure and installation	Dimensions 65 x 37 x 10 mm Weight 13 g Operating temperature range from -25°C to +50°C Operating humidity up to 95% Protection class IP50 Colours Black White	Complete set	SpaceControl Jeweller 1 x CR2032 battery Pre-installed Quick Start Guide