

REM25 & REM15

Wireless Remote Controls



REM25

The REM25 is a two-way wireless remote control that allows you to safely arm and disarm your Paradox security system and receive instant notification on your actions. It also allows you to verify the status of your system from a distance.

The REM25 wireless remote offers convenient fingertip control. With its two-way communication capabilities, the REM25 can initiate communication requests directly to your Paradox security system and receive acknowledgment confirmation for your request on the current status of your system. You can rest assured that your system is armed/disarmed and you can even view the status – remotely. With the press of a single button, the REM25 allows you to check the status, arm/disarm, and activate programmable outputs like lights, garage doors, and more. The REM25 offers secured encrypted disarm, meaning it cannot be copied by potential intruders.

With the REM25 you get visual and audio feedback regarding the result of your request (successful or failed action) and its comfortable keys makes operation effortless. It also contains a long-life lithium battery that is easy to replace and should last for years with normal operation use.

The REM25 also delivers system status when momentarily pressing the information (i) button. In return, the REM25 will initiate communication with your Paradox system and will provide you the status - Armed (red), Disarmed (green) Alarm or Alarm in Memory (flashing red).

The REM25 also offers a stylish, water-resistant design in two different colors: black and white and is available in a 433 MHz or 868 MHz version.

REM15

The REM15 wireless remote control is a one-way device that can transmit your actions to your Paradox security system. It provides the same functionality as the REM25 but without the convenience of feedback status and confirmation features.

Features

- ▶ Performs six (REM25) and five (REM15) different actions such as arming and disarming your system, enabling and disabling PGMs and providing system status
- ▶ Secured encrypted disarm function
- ▶ Action instant confirmation (REM25 only)
- ▶ System status display (REM25 only)
- ▶ Provides system status memory (REM25 only)
- ▶ Displays system status using visual (LED) and audible feedback (REM25 only)
- ▶ Supports StayD
- ▶ Available in 433 MHz or 868 MHz
- ▶ Water resistant
- ▶ Easily replaceable long-life lithium battery that lasts for years with normal operation use
- ▶ REM25 available colors: black and white
- ▶ REM15 available colors: black and white
- ▶ CE, EN 50131 approved

REM25 & REM15 Overview

REM25



REM15



Overview

▶ LED and Audio Functionality

The REM25 performs up to six different functions (REM15 up to five) that allow you to conveniently control your system at a distance. With the REM25, when an action is performed you will receive LED feedback and audible feedback results, thus making the operation of your system easy and effortless.

▶ Water Resistant

The REM25 and REM15 provide a water-resistant casing ensuring the remotes are protected against accidental splashes or rain.

▶ Easily Replaceable Battery

Both remotes have an easily removable and replaceable battery. Simply unscrew the back cover and replace with a new 3V lithium battery (CR2032).

Compatibility

For latest product compatibility visit paradox.com.

Technical Specifications

Specifications	Description
RF Frequency	433 or 868 MHz
Battery Type	1 x 3V lithium battery (CR2032)
Wireless Range for Typical Residential Environment	30m (100 ft) to 50m (164 ft) - line of sight (depending on receiver type)
Humidity	5 to 90%
Operating Temperature	-10 to 55 °C
Dimensions / Weight	REM25: 3.9 x 7.2 x 1.2 cm (1.5 x 2.8 x 0.5 in.) REM15: 3.9 X 6.6 X 1.1 cm (1.5 X 2.6 X 0.4 in.)
Certification	REM25: CE and C-Tick REM15: CE and EN 50131